

ABSTRACT OF THE DISCLOSURE

A memory module comprises a stab resistor between a pin and one end of a bus. A plurality of memory chips is connected to the bus between both ends thereof. A terminating resistor is connected to the other end of the bus. Stab resistance R_s of the stab resistor and terminating resistance R_{term} of the terminating resistor are given by:

$$R_s = (N - 1) \times Z_{effdim} / N, \text{ and}$$

$$R_{term} = Z_{effdim}$$

where N represents the number of the memory modules in a memory system; and Z_{effdim} , effective impedance of a memory chip arrangement portion consisting of the bus and the memory chips. In the memory system, the memory modules are connected to a memory controller on a motherboard in a stab connection style. Wiring impedance Z_{mb} of the motherboard is given by:

$$Z_{mb} = (2N - 1) \times Z_{effdim} / N^2.$$